BEGA

Floodlight

Project · Reference number

Product data sheet

Application

Floodlight with earthspike for temporary installation. For floodlighting plants, flowers and small woodlands, for wall and other surfaces and for various lighting purposes in the private garden.

Product description

Floodlight made of glass-fibre reinforced polyamide Silicone gasket Floodlight adjustable in two planes No tools are needed to adjust the operating position Ready for connection with 5 m connecting cable H05RN-F 2×1⁻⁻ and mains plug. 1 dummy screw gland Pg 7 Lampholder E 27 Safety class II Protection class · power plug IP X4 Protection against splash water Protection class · luminaire IP 65 Dust tight luminaires and protected against water jets ₫ 0.5 m 💹 minimum distance to the illuminated surface \mathbf{CE} – Conformity mark Weight: 1.1 kg

Light technique

Floodlight with rotationally symmetrical light distribution. Narrow beam when using spot type pressed glass reflector bulb giving point source beam over short distances. Half beam angle 12° PAR 38 · 60/80/120 W – Spot – Wide beam when using flood type pressed glass reflector bulb giving a wide beam over short distance. Half beam angle 30° PAR 38 · 60/80/120 W – Flood – Date





Lamps

 $\begin{array}{l} 2 \text{ Pressed glass reflector bulbs} \\ \text{PAR 38} \cdot & 60 \ \text{W} \cdot \text{E 27} \\ \text{PAR 38} \cdot & 80 \ \text{W} \cdot \text{E 27} \\ \text{PAR 38} \cdot & 120 \ \text{W} \cdot \text{E 27} \\ \text{PAR 38} \cdot & 120 \ \text{W} \cdot \text{E 27} \\ \text{Narrow beam - Spot} \cdot & 12^{\circ} \\ \text{Broad beam - Flood} \cdot & 30^{\circ} \end{array}$

800 lm 1100 lm 2° 0°

Please note the lamp manufacturers' operating instructions.

Accessories

	Permanent connecting pillar
600 lm	for electrical connection of portable garden
800 lm	luminaires and electric gardening tools.
1100 lm	They are used for switching tools and lighting
	equipment.
perating	70375 with 2 socket outlets
	70376 with 1 socket outlet + 1 switch
	70377 with 4 socket outlets
	70378 with 3 socket outlets + 1 switch

For the accessories a separate instructions for use can be provided upon request.

77 942

□ IP 65